

Method and apparatus for the nondestructive measurement of the thickness of thin layers

5 The invention relates to a method for the nondestructive measurement of the thickness of thin layers with a probe according to the precharacterizing clause of Claim 1 and to an apparatus according to the precharacterizing clause of Claim 10.

10 Curved and coated surfaces can be encountered in particular in aircraft construction, in automobiles, in moulded parts, in the area of household articles, in pipeline construction, on Venetian blinds and in the case of many other coated objects of measurement. In
15 the area of nuclear power as well, oxide layers on zirconium heat exchanger tubes, in the range of 20 μm on tubes approximately 12 mm in diameter, are to be measured.

20 Known tactile measuring methods, which are based for example on the eddy current principle, are influenced very strongly by the shape of the object of measurement. For this reason, when there are different curvatures a calibration must take place, which is
25 time-consuming and may lead to errors, in particular because changes in curvature are not taken into account.

DE 41 19 903 A1 discloses a method and an apparatus for
30 the measurement of thin layers, making it possible that the undesired dependence of the measured value on the geometrical shape of the object of measurement can be eliminated in a broad range. This means that it is made possible for thin layers to be measured even on
35 curved surfaces of objects of measurement. These are layer thicknesses from just a few μm to several 100 μm . This nondestructive layer thickness measurement relies on the eddy current principle, which is based on changes of a low-frequency or high-frequency
40 electromagnetic field in dependence on a layer applied

to the object of measurement. Provided for this is an apparatus which has a first coil device on a ferrite core. An outer sleeve, which surrounds the first coil device, receives a second coil device, lying outside.

5 The core receiving the first coil device has at its lower end a hemispherical placement dome of abrasion-resistant material.

To ascertain the layer, the probe is placed on the
10 object of measurement. The two coil devices are excited with frequencies which are different at the same time and consequently emit two signals of different frequencies during the measurement, which are evaluated by a suitable circuit in order to calculate
15 the layer thickness. The layer thickness is ascertained in accordance with the equations specified in DE 41 19 903 A1.

The invention is thus based on the object of improving
20 the quality of the ascertained layer thickness values in the nondestructive measurement of the thickness of thin layers.

This object is achieved by the features of Claim 1.
25 The sequential excitation of at least two coil devices allows nondestructive emission of the measuring signals to take place from the coil devices to an evaluation unit. The successive excitation of the coil devices with the respective frequency allows a signal
30 uninfluenced by the respectively neighbouring other coil device to be recorded by the evaluation unit during the measurement and also unequivocally assigned to each coil device. As a result, overshooting or sympathetic excitation of the neighbouring coil device
35 can be eliminated, whereby the signal emission can take place free from disturbing parameters.

According to a further advantageous refinement of the method, it is provided that the coils are excited with

high frequency. As a result, changes of the alternating electromagnetic field when a probe head approaches the object of measurement can be utilized as a measuring effect for the measurement. When high-
5 frequency fields are used, the layers to be measured are electrically non-conducting, such as paint for example, or weakly conducting, such as chromium or the like for example.

- 10 According to a further advantageous refinement of the method, it is provided that the frequency signals coming from the first and at least second coil device, which are emitted at separate times from one another, are restricted in the duration of the emission of the
15 signals by field-effect transistors. As a result, a separation between the emitted frequency signal of the first coil device and of the at least second coil device can be ensured, whereby an exact recording and assignment of the measuring signals can be achieved.
- 20 As a result, mutual influencing or superimposing can be prevented, even during the transmission of the signals to the evaluation unit. The activation of the coil devices and of the field-effect transistors, via which the measuring signals are passed on to an evaluation
25 unit, can take place in a defined time window, whereby the assigning of the measuring signals is also made possible.

- According to a further advantageous refinement of the
30 method, it is provided that the signals emitted by the coil devices are evaluated independently of one another. For example, a signal substantially determining the layer thickness may be recorded by a first coil device, while for example a signal
35 determining the curvature of the object of measurement may be recorded through the other coil device. The separate evaluation allows an exact calculation of the two measurement variables to be obtained, whereby the subsequent ascertainment of the measured value can take

place by the formulae - as revealed by DE 41 19 903 A1
- with a higher degree of accuracy.

The separation of the signals of the coil devices
5 advantageously allows the excitation of the coil
devices to take place with the same frequency, whereby
further simplification of the structural setup of the
control system can be achieved.

10 According to a further advantageous refinement of the
method, it is provided that, for carrying out a
measurement, a first coil device is excited by a first
circuit and a second coil device is excited in a second
circuit one after the other by means of a flipflop
15 circuit. The advantageously provided field-effect
transistors make it possible to ensure by the circuitry
used that the sequential activation of the coil device
is made possible for the emission of frequency signals.
It is advantageously provided that the circuits of the
20 coil devices are identically designed. As a result,
the setup of the circuit can be of a simple
arrangement.

According to a further advantageous refinement of the
25 method, it is provided that the frequency signals are
passed to the evaluation unit via a compensator. This
makes it possible for the phase relationship of the
frequency signals to be set in such a way that the
undesired dependence of the measuring signals on the
30 electrical conductivity of the base material is largely
eliminated.

Consequently, the method according to the invention for
the nondestructive measurement of the thickness of thin
35 layers allows the effect to be achieved that the
influence on the measured values at least of disturbing
parameters such as the curvature of the surfaces and
the conductivity of the object of measurement, which
have particularly critical effects in the measurement

of thin layers in the range of just a few μm , is eliminated virtually completely.

The apparatus according to the invention, which is intended in particular for carrying out the method, has in a housing a ferritic cup-type core, which receives a first coil device and has on a pin lying in the first coil device a hemispherical placement dome and receives a further coil device, outside the cup-shaped core, concentrically with respect to the first coil device. The coil devices, which are arranged fixedly in relation to each other and advantageously have a common centre axis, allow an exact ascertainment to be obtained, since the range of action of the first and second coil devices emanates from the common geometrical axis on account of the common placement point of the hemispherical placement dome. The first or inner coil device is in this case designed to be sensitive to layer thicknesses and the outer or second coil device is designed to be sensitive to curvature.

Further advantageous designs are specified in the further claims.

A preferred embodiment of the measuring probe and of a circuit for carrying out the method according to the invention are explained in more detail in the following description. In the figures:

Figure 1 shows a perspective view of a measuring probe,

Figure 2 shows a schematic cross section of a probe head of the measuring probe,

Figure 3 shows a view from below of the measuring head according to Figure 2,

Figure 4 shows a schematic representation of

components of the measuring probe which can be fitted one inside the other,

5 Figure 5 shows a schematic representation of the measuring probe in measurement on a curved surface,

10 Figure 6 shows a schematic representation of the circuit for carrying out the measuring method and

15 Figure 7 shows a diagram of a characteristic curve which shows a comparison of measured values ascertained in a way according to the prior art and in a way according to the invention.

20 A device designed as a measuring probe 11 is represented perspectively in Figure 1. The measuring probe 11 can be connected via a cable 12 and a connection plug 13 to an evaluation device (not represented in any more detail). The measuring probe 11 has a probe head 14, which is surrounded by a sleeve 16. The probe head 14 is arranged axially movably with respect to the guide sleeve 17. This is described in 25 more detail below in Figure 4.

30 A schematic cross section of the probe head 14 is represented greatly enlarged in Figure 2. The corresponding view from below is represented in Figure 3. The probe head 14 has a housing 18, in which a measuring system is embedded in a preferably non-magnetic composition 19. The measuring system comprises a cup-type core 21, which has central pin 23 in a geometrical axis 22. A first or inner coil device 35 24 is provided concentrically with respect to the central pin 23. Provided on the end face of the cup-type core 21 is, for example, an insulating disc 26. The cup-type core 21 has on the end face of the central pin 23 a hemispherical placement dome 27, which is

formed from abrasion-resistant material, such as for example a ruby, and at least a non-magnetic material. The placement surface of the hemispherical placement dome 27 is of a curved design, the deepest point of which lies in the geometrical axis 22. The cup-like core 21 has preferably diametrically opposing slits 28, through which connection lines of the inner coil device 24 are led into a rear region of the probe head 14, which in turn is connected to an electronic circuit 50. Arranged on an outer shell 29 of the cup-type core 21 is a second or outer coil device 31. The coil devices 24, 31 are immovable on the cup-type core 21, for example cast firmly in place, so that the probe head 14 is designed as a solid unit. The end faces of the coil devices 24, 31 pointing towards the object of measurement are arranged on a common plane. Similarly, the end face of the housing 18 advantageously lies in this plane. The measuring probe 11 has dimensionally, for example, a typical diameter of a fountain pen, in which the actual measuring system with a diameter of approximately 2 mm is movably fitted.

The layer thicknesses of interest mainly lie in the range of several μm to 100 μm . However, thicker coatings which reach into the mm range can also be recorded.

A setup of the measuring probe 11 is represented in Figure 4 in a kind of exploded representation. The probe head 14 has a first cylindrical portion 33, which merges with a second portion 34 of a smaller diameter. The cylindrical portion 34 advantageously has a thread, so that an easy way of fitting it with respect to the intermediate sleeve 36 is obtained. In this portion is a printed-circuit board, on which the circuit 50 according to the invention, represented in Figure 6, is provided. This structural unit is received by an intermediate sleeve 36, which for its part is received by a guide sleeve 17 in a resiliently compliant manner

by means of a preferably helical spring 37. The guide sleeve 17 has a receiving portion 38, on which the sleeve 16 can be fitted. The resilient mounting of the intermediate sleeve 36 in the guide sleeve 17 allows
5 the probe head 14, which in a starting position protrudes from the end face of the sleeve 16, to move into the sleeve. This also serves the purpose that the hemispherical placement dome 27 makes placement contact in extension of the geometrical axis 22, as is
10 described below in Figure 5.

The intermediate sleeve 36 is guided axially movably in the guide sleeve 17. Furthermore, an anti-twisting means is provided, such as for example a tongue-and-groove connection or a spring element 37, which is
15 arranged and braced against the intermediate sleeve 36 and which runs in a groove of the guide sleeve 17. The connection lines to the guide sleeve 17 are fixed by means of an intermediate piece 39. At the same time,
20 this may form a strain relief.

The spring 37, arranged between the intermediate sleeve 36 and the guide sleeve 17, is at least slightly biased, so that during the measurement of the curved
25 surface the probe head 14 lies with an at least slight pressing force on the surface or the layer to be measured. However, this force is small in relation to the hardness of the layer, so that there are no impressions or damage after the measurement of the
30 layer thickness.

The measurement of a layer thickness on a curved surface is represented by way of example in Figure 5. The sleeve 16 has on its end face a preferably
35 prismatic recess 41, allowing the effect to be achieved that, when the measuring probe 11 is placed onto the curved surface, a secured and defined contact of the measuring probe 11 can be created with respect to the surface. The size and nature of the recess 41 can be

adapted to different objects of measurement. This also allows the measuring probe 11 to be centred on the cylindrical or curved surface, whereby a controlled measurement can be carried out. The probe head 14 is
5 in this case retracted into the sleeve 16 from its starting position, as represented for example in Figure 1, along the geometrical axis 22. The hemispherical placement dome 27 is held at least under a slight pressure on the surface 42 of the object of measurement
10 by the helical spring 37. Immediately after the measuring probe 11 has been placed on the object of measurement, measurement of the thickness of thin layers can be carried out.

15 Such a measurement is described below on the basis of the circuit 50 according to Figure 6.

The circuit 50 comprises two virtually identical oscillating circuits 51 and 52. The mode of operation
20 is described by way of example with reference to circuit 51, which is assigned to the inner winding or the coil device 24. The series oscillating circuit, comprising a capacitor 53 of this coil device 24, forms in connection with a dual-gate field-effect transistor
25 54 an active series resonance circuit. This is possible because, in the case of series resonance, a distinct overvoltage occurs at the coil device 24 in comparison with the high-frequency voltage which is produced at a resistor 56. This satisfies the
30 resonance condition. The coil device 24 is at an earth potential on one side. The voltage produced at the coil device 24 is fed via a resistor 57 and a variable resistor 58 to the gate 2 of the transistor 54. The variable resistor 58 can be used in connection with the
35 capacitor to perform a phase rotation in such a way that the undesired dependence of the measured value on the conductivity of the base material is suppressed almost completely. A capacitor 59 determines the feedback and is chosen in such a way that a virtually

sinusoidal voltage with a very small harmonic content is produced at the resistor 56. This makes it possible for spurious radiation to be largely suppressed. If the gate 1 of the transistor 54 is switched to low, the resonance condition is no longer satisfied and the oscillation decays very quickly. If the probe head 14 is brought towards a metallic base metal, eddy currents are generated in it, detuning the oscillating circuit 51. The approaching of the coil device 24 corresponds to the measuring effect of the layer thickness. The measuring effect is linked to the layer thickness by a non-linear function. The layer is generally electrically insulating, so that eddy currents are generated only in the base material. However, with the circuit 50, a measurement is also possible according to the invention when a poorly conducting, non-magnetic layer, for example chromium, is electrolytically deposited on non-magnetic base material, for example aluminium, which has a distinctly better conductivity.

The circuit 52 operates in a way analogous to the circuit 51. However, the coil device 31, which is preferably excited with the same frequency as the coil device 24, reacts substantially only to curvature, the curvature-induced changing frequency serving to compensate the influence of the curvature in a way corresponding to DE 41 19 903 A1. The excitation frequencies of the coil devices 24, 31 lie for example in the range from 5 to 30 MHz. Provided in a signal input line 56 are two inverters 62, 63, which ensure that only one transistor 54 of a circuit 51, 52 is enabled for oscillation. If the switching point 64 is at high (1), only the circuit 51 is enabled for oscillation. If the switching point 64 is at low (0), only the circuit 52 is enabled. The two dual-gate field-effect transistors 54 are connected via a line 60 to an identical d.c. supply voltage of, for example, 5 V, which is fed via a small inductance 66, in order to activate the latter. Alternatively, it is possible

to dispense with the gate 1 of the field-effect transistors 54 and for the transistors 54 to be alternately switched on and off by two intermittently switched lines. This type of switching is possible by means of high-speed semiconductor switches.

The resonance of the two sequentially connected transistors 54 has the effect that the respective resonant frequency can be picked up by the circuit 51 and 52 at the resistor 68 via the inductance 66, which forms a series oscillating circuit 65 with a capacitor 67. This allows signals of the respective coil device 24, 31 to be detected and picked up, recorded and evaluated by the downstream series circuit 65 via a switching point 70. The high-frequency signals are superimposed on the d.c. voltage supply line 61. For the evaluation, a change between the coil devices 24, 31 takes place for example 10 times every second, so that at least 100,000 oscillations are available for forming the measured value. A smaller number would also suffice.

In connection with the switching state at the switching point 64, the resonance is uniquely defined by the circuits 51 and 52, so that the two signals of the circuits 51, 52 can be brought together, as described in DE 41 19 903 A1, in a downstream circuit. The circuit shown may be constructed using SMD technology and be integrated directly in the probe 11, as shown in Figure 4.

Represented in Figure 7 is a diagram of a characteristic curve, which represents the percentage accounted for by the curvature in dependence on the diameter of the curved surface on which a measurement of the layer thickness has taken place. A characteristic curve 81 represents the measured values which have until now been ascertained by measuring probes and circuits known from the prior art. It can

be seen from this that the curvature error previously made up a considerable percentage, particularly in the case of very small diameters. The apparatus according to the invention and the method according to the invention ascertain measured values according to a characteristic curve 82, the percentage curvature error of which is reduced to a considerable extent. This makes it clear to what extent an improvement over the prior art has been achieved. This is of great significance for the user. For example, it allows a substantial increase in measuring accuracy to be achieved in quality control.

Claims

1. Method for the nondestructive measurement of the thickness of thin layers with a probe (11), which
5 has a first coil device (14) on an inner core, the geometrical centre (22) of which coil device and the geometrical centre of at least a second coil device (31) coincide, the at least second coil device (31) partially surrounding the first coil
10 device (24), with an evaluation unit, to which signals of the coil devices (24, 31) are emitted during a measurement for ascertaining the layer thickness, characterized in that a circuit (50) is provided, by which the first and the at least
15 second coil device (24, 31) are excited sequentially during a measurement.
2. Method according to claim 1, characterized in that
20 the coil devices (24, 31) are excited with high frequency.
3. Method according to claim 1 or 2, characterized in
25 that the frequency signals coming from the first and at least second coil device (24, 31), which are emitted at separate times from one another, are limited by the period for the emission of the frequency signals of each coil device (24, 31) by
30 means of transistors (54) which are preferably activated by the circuit (50) in analogy with the coil devices (24, 31).
4. Method according to claim 1, characterized in that
35 the signals emitted by the coil devices (24, 31) are unequivocally assigned to the respective coil device (24, 31) and evaluated independently of one another by a series oscillating circuit (65).

**UNITED STATES PATENT AND TRADEMARK OFFICE
DOCUMENT CLASSIFICATION BARCODE SHEET**



Claims

frequency.

- 5 6. Method according to claim 1, characterized in that the first coil device (24) is excited with a frequency between 8 and 20 MHz, and in that the other coil device (31) is excited with a frequency between 4 and 12 MHz.
- 10 7. Method according to claim 1, characterized in that the oscillations of the coil devices (24, 31) of the measuring field that is changing during the measurement are interrogated at least twice per second.
- 15 8. Method according to claim 1, characterized in that the first coil device (24) has a circuit (51) and the second coil device (31) has a circuit (52), which are connected parallel to each other, and a flipflop circuit (62, 53) is provided, by which the transistor (54) respectively assigned to the coil
20 devices (24, 31) is advantageously switched time-dependently.
- 25 9. Method according to claim 1, characterized in that the frequency signal emitted by the coil device (24, 31) is passed to the evaluation unit via a compensator (58).
- 30 10. Apparatus, in particular for carrying out the method according to one of the preceding claims, with a housing (18), with a first coil device (24) and a second coil device (31) and with a hemispherical placement dome (27), characterized in that a probe head (14) with a ferritic cup-type
35 core (21), which receives the first coil device (24) close to a common geometrical axis (22), is provided and in that the cup-type core (21) has in the common axis (22) a pin (23) which lies within the first coil device (24) and on the end face of

which the hemispherical placement dome (27), which projects at least partially from the end face of the coil device (14), is provided, and in that a second coil device (31) is provided concentrically outside the cup-type core (21).

5

11. Apparatus according to claim 10, characterized in that the number of turns of the first coil device (24) is equal to or less than that of the second coil device (31).

10

12. Apparatus according to one of claims 10 or 11, characterized in that the first and second coil devices (24, 31) are arranged fixedly in relation to each other and are preferably embedded in a casting composition.

15

13. Apparatus according to claim 10, characterized in that the first and second coil devices (24, 31) are arranged in one plane with respect to the end face of the probe head (14).

20

14. Apparatus according to claim 10, characterized in that the cup-type core (21) has at least one lateral slit (28) for the leading through of connection lines.

25

15. Apparatus according to claim 10, characterized in that the probe head (14) is mounted such that it can be axially displaced in a guide sleeve (17) and retracted with respect to a protective sleeve (16) arranged fixedly in relation to the guide sleeve (17).

30

16. Apparatus according to claim 15, characterized in that the protective sleeve (16) has a recess (41), which is preferably prismatically formed, on an end face pointing towards the probe head (14).

35

17. Apparatus according to claim 15 or 16,
characterized in that the probe head (14) is
retractable into the protective sleeve (16) against
a spring force, and in that a spring element (37)
5 is arranged with at least slight biasing with
respect to the guide sleeve (17).
18. Apparatus according to claim 10, characterized in
that the first coil device (24) is designed such
10 that it is sensitive to layer thicknesses and the
at least one further coil device (31) is designed
such that it is sensitive to curvature.
19. Circuit for the separate evaluation of two
15 measuring signals, in particular for carrying out
the method according to one of claims 1 to 9,
characterized in that the detuning of a respective
inductance (24, 31) results in a change in
frequency, one inductance (24) being influenced
20 primarily by the layer thickness and the other
inductance (31) being influenced primarily by the
curvature of the object of measurement.
20. Circuit according to claim 19, characterized in
25 that the two inductances (24, 31) have a common
earth and the frequency can be coupled out at a
switching point (70) in unequivocal assignment to
the corresponding frequency signal.